

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0001	NumberOfMeasurementTypes	uint8	max 32	F		R V	M
0x0002	Accuracy	list[MeasurementAccuracyStruct]	1 to NumberOfMeasurementTypes	F		R V	M
0x0003	Ranges	list[MeasurementRangeStruct]	0 to NumberOfMeasurementTypes	Q	empty	R V	O
0x0004	Voltage	voltage-mV	-2^{62} to 2^{62}	Q X	null	R V	O
0x0005	ActiveCurrent	amperage-mA	-2^{62} to 2^{62}	Q X	null	R V	O
0x0006	ReactiveCurrent	amperage-mA	-2^{62} to 2^{62}	Q X	null	R V	[ALTC]
0x0007	ApparentCurrent	amperage-mA	-2^{62} to 2^{62}	Q X	null	R V	[ALTC]
0x0008	ActivePower	power-mW	-2^{62} to 2^{62}	Q X		R V	M
0x0009	ReactivePower	power-mVAR	-2^{62} to 2^{62}	Q X	null	R V	[ALTC]
0x000A	ApparentPower	power-mVA	-2^{62} to 2^{62}	Q X	null	R V	[ALTC]
0x000B	RMSVoltage	voltage-mV	-2^{62} to 2^{62}	Q X	null	R V	[ALTC]
0x000C	RMSCurrent	amperage-mA	-2^{62} to 2^{62}	Q X	null	R V	[ALTC]
0x000D	RMSPower	power-mW	-2^{62} to 2^{62}	Q X	null	R V	[ALTC]
0x000E	Frequency	int64	0 to 1000000	Q X	null	R V	[ALTC]
0x000F	HarmonicCurrents	list[HarmonicMeasurementStruct]	max 25	Q X		R V	HARM