

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0010	HarmonicPhases	list[HarmonicMeasurementStruct]	max 25	Q X		R V	PWRQ
0x0011	PowerFactor	int64	-10000 to 10000	Q X	null	R V	[ALTC]
0x0012	NeutralCurrent	amperage-mA	-2^{62} to 2^{62}	Q X	null	R V	[POLY]

2.13.6.1. PowerMode Attribute

This SHALL indicate the current mode of the server. For some servers, such as an EV, this may change depending on the mode of charging or discharging.

2.13.6.2. NumberOfMeasurementTypes Attribute

This SHALL indicate the maximum number of measurement types the server is capable of reporting.

2.13.6.3. Accuracy Attribute

This SHALL indicate a list of [accuracy specifications](#) for the [measurement types](#) supported by the server. There SHALL be an entry for [ActivePower](#), as well as any other measurement types implemented by this server.

2.13.6.4. Ranges Attribute

This SHALL indicate a list of [measured ranges](#) for different [measurement types](#). Each measurement type SHALL have at most one entry in this list, representing the range of measurements in the most recent measurement period.

The reporting interval of this attribute SHALL be manufacturer dependent. The server MAY choose to omit publication of deltas considered not meaningful.

The server SHALL NOT mark this attribute ready for report if the last time this was done was more recently than 1 second ago.

The server MAY delay marking this attribute ready for report for longer periods if needed, however the server SHALL NOT delay marking this attribute as ready for report for longer than 60 seconds.

2.13.6.5. Voltage Attribute

This SHALL indicate the most recent [Voltage](#) reading in millivolts (mV).

The reporting interval of this attribute SHALL be manufacturer dependent. The server MAY choose to omit publication of deltas considered not meaningful.