

2.13.6.14. RMSPower Attribute

This SHALL indicate the most recent [RMSPower](#) reading in milliwatts (mW).

A positive value represents power imported, while a negative value represents power exported.

The reporting interval of this attribute SHALL be manufacturer dependent. The server MAY choose to omit publication of deltas considered not meaningful.

The server SHALL NOT mark this attribute ready for report if the last time this was done was more recently than 1 second ago.

The server MAY delay marking this attribute ready for report for longer periods if needed, however the server SHALL NOT delay marking this attribute as ready for report for longer than 60 seconds.

If the RMS power cannot be measured, a value of null SHALL be returned.

2.13.6.15. Frequency Attribute

This SHALL indicate the most recent [Frequency](#) reading in millihertz (mHz).

The reporting interval of this attribute SHALL be manufacturer dependent. The server MAY choose to omit publication of deltas considered not meaningful.

The server SHALL NOT mark this attribute ready for report if the last time this was done was more recently than 1 second ago.

The server MAY delay marking this attribute ready for report for longer periods if needed, however the server SHALL NOT delay marking this attribute as ready for report for longer than 60 seconds.

If the frequency cannot be measured, a value of null SHALL be returned.

2.13.6.16. HarmonicCurrents Attribute

This SHALL indicate a list of [HarmonicMeasurementStruct](#) values, with each [HarmonicMeasurementStruct](#) representing the harmonic current reading for the harmonic order specified by [Order](#).

The reporting interval of this attribute SHALL be manufacturer dependent. The server MAY choose to omit publication of deltas considered not meaningful.

The server SHALL NOT mark this attribute ready for report if the last time this was done was more recently than 1 second ago.

The server MAY delay marking this attribute ready for report for longer periods if needed, however the server SHALL NOT delay marking this attribute as ready for report for longer than 60 seconds.

2.13.6.17. HarmonicPhases Attribute

This SHALL indicate a list of [HarmonicMeasurementStruct](#) values, with each [HarmonicMeasurementStruct](#) representing the most recent phase of the harmonic current reading for the harmonic order specified by [Order](#).