

Command execution SHALL NOT continue beyond the Options processing if all of these criteria are true:

- The On/Off cluster exists on the same endpoint as this cluster.
- The OnOff attribute of the On/Off cluster, on this endpoint, is FALSE.
- The value of the ExecuteIfOff bit is 0.

3.2.7.11.1. ExecuteIfOff Bit

- 0 = Do not execute command if the OnOff attribute in the On/Off cluster is FALSE.
- 1 = Execute command if the OnOff attribute in the On/Off cluster is FALSE.

3.2.7.12. EnhancedCurrentHue Attribute

This attribute SHALL indicate the non-equidistant steps along the [CIE 1931 color triangle](#), and it provides 16-bits precision.

The upper 8 bits of this attribute SHALL be used as an index in the implementation specific XY lookup table to provide the non-equidistant steps. The lower 8 bits SHALL be used to interpolate between these steps in a linear way in order to provide color zoom for the user.

To provide compatibility with clients not supporting EHUE, the CurrentHue attribute SHALL contain a hue value in the range 0 to 254, calculated from the EnhancedCurrentHue attribute.

Changes to this attribute SHALL only be marked as reportable in the following cases:

- At most once per second or
- At the end of the movement/transition.

3.2.7.13. EnhancedColorMode Attribute

This attribute SHALL indicate which attributes are currently determining the color of the device.

To provide compatibility with clients not supporting EHUE, the original ColorMode attribute SHALL indicate CurrentHue and CurrentSaturation when the light uses the EnhancedCurrentHue attribute. If the ColorMode attribute is changed, its new value SHALL be copied to the EnhancedColorMode attribute.

3.2.7.14. ColorLoopActive Attribute

This attribute SHALL indicate the current active status of the color loop. If this attribute has the value 0, the color loop SHALL NOT be active. If this attribute has the value 1, the color loop SHALL be active.

3.2.7.15. ColorLoopDirection Attribute

This attribute SHALL indicate the current direction of the color loop. If this attribute has the value Decrement, the EnhancedCurrentHue attribute SHALL be decremented. If this attribute has the value Increment, the EnhancedCurrentHue attribute SHALL be incremented.