

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	ColorTemperatureMireds	uint16	max 65279			M
1	TransitionTime	uint16	max 65534			M
2	OptionsMask	OptionsBitmap	desc			M
3	OptionsOverride	OptionsBitmap	desc			M

3.2.8.14.1. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.14.2. Effect on Receipt

On receipt of this command, a device SHALL set the value of the ColorMode attribute, where implemented, to 2 (ColorTemperatureMireds), and SHALL then move from its current color to the color given by the ColorTemperatureMired field.

The movement SHALL be continuous, i.e., not a step function, and the time taken to move to the new color SHALL be equal to the TransitionTime field, in 1/10ths of a second.

By definition of this color mode, the path through color space taken during the transition is along the 'Black Body Line'.

If the ColorTemperatureMireds field is less than the value of the ColorTempPhysicalMinMireds attribute, the value of the ColorTempPhysicalMinMireds attribute SHALL be used as the final target for the ColorTemperatureMireds attribute.

If the ColorTemperatureMireds field is greater than the value of the ColorTempPhysicalMaxMireds attribute, the value of the ColorTempPhysicalMaxMireds attribute SHALL be used as the final target for the ColorTemperatureMireds attribute.

3.2.8.15. EnhancedMoveToHue Command

This command allows the light to be moved in a smooth continuous transition from their current hue to a target hue.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	EnhancedHue	uint16	all			M