

ID	Name	Type	Constraint	Quality	Fallback	Conformance
2	Options-Mask	Options-Bitmap	desc			M
3	OptionsOverride	Options-Bitmap	desc			M

3.2.8.16.1. MoveMode Field

This field SHALL indicate the mode of movement, as described in the [MoveHue](#) command.

3.2.8.16.2. Rate field

This field SHALL indicate the rate of movement in steps per second. A step is a change in the extended hue of a device by one unit.

3.2.8.16.3. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.16.4. Effect on receipt

On receipt of this command,

- If the MoveMode field is set to 1 (Up) or 3 (Down)
 - If the Rate field has a value of zero, the command has no effect and a response SHALL be returned with the status code set to INVALID_COMMAND.
 - Otherwise, a device SHALL set the ColorMode attribute to 0 (CurrentHueAndCurrentSaturation) and set the EnhancedColorMode attribute to the value 3 (EnhancedCurrentHueAndCurrentSaturation). The device SHALL then move from its current enhanced hue in an up or down direction in a continuous fashion, as detailed in the table.
- If the MoveMode field is set to 0 (Stop), the Rate field SHALL be completely ignored.

MoveMode	Action on Receipt
Stop	If moving, stop, else ignore the command (i.e., the command is accepted but has no effect). This SHALL stop any ongoing hue and/or saturation transition.
Up	Increase the device's enhanced hue at the rate given in the Rate field. If the enhanced hue reaches the maximum allowed for the device, wraparound and proceed from its minimum allowed value.