

MoveMode	Action on Receipt
Down	Decrease the device's enhanced hue at the rate given in the Rate field. If the hue reaches the minimum allowed for the device, wraparound and proceed from its maximum allowed value.

3.2.8.17. EnhancedStepHue Command

This command allows the light to be moved in a stepped transition from their current hue, resulting in a linear transition through XY space.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	StepMode	StepModeEnum	desc			M
1	StepSize	uint16	all			M
2	Transition-Time	uint16	max 65534			M
3	Options-Mask	Options-Bitmap	desc			M
4	OptionsOverride	Options-Bitmap	desc			M

3.2.8.17.1. StepMode Field

This field SHALL indicate the mode of the step to be performed, as described in the [StepHue](#) command.

3.2.8.17.2. StepSize Field

This field SHALL indicate the change to be added to (or subtracted from) the current value of the device's enhanced hue.

3.2.8.17.3. TransitionTime Field

The field SHALL indicate, in units of 1/10ths of a second, the time that SHALL be taken to perform the step. A step is a change to the device's enhanced hue of a magnitude corresponding to the StepSize field.

NOTE

Here TransitionTime data field is of data type uint16, while the TransitionTime data field of the StepHue command is of data type uint8.

3.2.8.17.4. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).