

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PINCode	octstr				[COTA & PIN]

5.2.10.1.1. PINCode Field

If the `RequirePINforRemoteOperation` attribute is `True` then `PINCode` field SHALL be provided and the door lock SHALL NOT grant access if it is not provided.

If the `PINCode` field is provided, the door lock SHALL verify `PINCode` before granting access regardless of the value of `RequirePINForRemoteOperation` attribute.

When the `PINCode` field is provided an invalid PIN will count towards the `WrongCodeEntryLimit` and the `UserCodeTemporaryDisableTime` will be triggered if the `WrongCodeEntryLimit` is exceeded. The lock SHALL ignore any attempts to lock/unlock the door until the `UserCodeTemporaryDisableTime` expires.

5.2.10.2. UnlockDoor Command

This command causes the lock device to unlock the door. This command includes an optional code for the lock. The door lock MAY require a code depending on the value of the [RequirePINForRemoteOperation](#) attribute.

NOTE

If the attribute `AutoRelockTime` is supported the lock will transition to the locked state when the auto relock time has expired.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PINCode	octstr				[COTA & PIN]

5.2.10.2.1. PINCode Field

See [Section 5.2.10.1.1, “PINCode Field”](#).

5.2.10.3. UnlockWithTimeout Command

This command causes the lock device to unlock the door with a timeout parameter. After the time in seconds specified in the timeout field, the lock device will relock itself automatically. This timeout parameter is only temporary for this message transition and overrides the default relock time as specified in the `AutoRelockTime` attribute. If the door lock device is not capable of or does not want to support temporary Relock Timeout, it SHOULD NOT support this optional command.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Timeout	uint16				M
1	PINCode	octstr				[COTA & PIN]