

If the closure supports the MotionLatching (LT) feature, it SHALL either fulfill the latch request and update OverallTargetState.Latch or, if the "[LatchControlModes](#)" attribute specifies that manual intervention is required to latch - respond with INVALID_IN_STATE and remain in its current state.

5.4.8.2.3. Speed Field

This field SHALL indicate a desired overall speed of motion, as defined in the ThreeLevelAutoEnum.

If the field is present but its value is not within constraints, then:

- If the Speed(SP) feature is not supported, the value of this field SHALL be ignored.
- If the Speed(SP) feature is supported, a status code of CONSTRAINT_ERROR SHALL be returned.

If the closure supports the Speed(SP) feature, it SHALL set the Speed field of the OverallCurrentState attribute to the new speed.

5.4.8.2.4. Effect on Receipt

If this command is received in any state other than Moving, WaitingForMotion, or Stopped, a status code of INVALID_IN_STATE SHALL be returned.

If a field is present in the command, but its associated feature is not supported, that field SHALL be treated as absent for the purposes of command processing. Specifically:

- If the Position field is present but the Positioning (PS) feature is not supported, the Position field SHALL be ignored and have no effect.
- If the Latch field is present but the MotionLatching (LT) feature is not supported, the Latch field SHALL be ignored and have no effect.
- If the Speed field is present but the Speed (SP) feature is not supported, the Speed field SHALL be ignored and have no effect.

In all such cases, the presence of an unsupported field SHALL NOT trigger errors or state changes.

If this command requests a position change while the Latch field of the [OverallCurrentState](#) attribute is True (Latched), and the Latch field of this command is not set to False (Unlatched), a status code of INVALID_IN_STATE SHALL be returned.

Otherwise, on success:

- A status code of SUCCESS SHALL be returned.
- The [OverallTargetState Attribute](#) SHALL be updated with the requested values for Position, Latch and/or Speed.
- If all field values in the command match the corresponding field values in [OverallCurrentState Attribute](#), the [MainState Attribute](#) SHALL be set to Stopped, and no further action SHALL be taken.
- If the closure is not able to move e.g. due to power limitation, the [MainState](#) attribute SHALL be set to WaitingForMotion, else the [MainState Attribute](#) SHALL be set to Moving.