

string of decimal numbers (11 characters) or the Passcode portion of the Manual Pairing Code encoded as a string of decimal numbers (8 characters).

The server SHALL implement rate limiting to prevent brute force attacks. No more than 10 unique requests in a 10 minute period SHALL be allowed; a command response status of FAILURE should be sent for additional commands received within the 10 minute period. Because access to this command is limited to nodes with Admin-level access, and the user is involved when obtaining the Setup PIN, there are in place multiple obstacles to successfully mounting a brute force attack. A Content App that supports this command SHALL ensure that the Temporary Account Identifier used by its clients is not valid for more than 10 minutes.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	TempAccountIdentifier	string	16 to 100			M
1	SetupPIN	string	min 8			M
2	Node	node-id				O

6.2.4.3.1. TempAccountIdentifier Field

This field SHALL specify the client's temporary account identifier.

6.2.4.3.2. SetupPIN Field

This field SHALL provide the Setup PIN as a text string at least 8 characters in length.

NOTE

Newer cluster clients should be aware that AccountLogin cluster revision 1 specified an 11 digit minimum length.

6.2.4.3.3. Node Field

This optional field SHALL provide the Node ID of the Client. This field can be used by the Content App to keep track of Nodes which currently have access to it.

6.2.4.4. Logout Command

The purpose of this command is to instruct the Content App to clear the current user account. This command SHOULD be used by clients of a Content App to indicate the end of a user session.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Node	node-id				O

6.2.4.4.1. Node Field

This optional field SHALL provide the Node ID of the Client. This field can be used by the Content App to keep track of Nodes which currently have access to it.