

Value	Name	Conformance
0x6B	PowerToggleFunction	M
0x6C	PowerOffFunction	M
0x6D	PowerOnFunction	M
0x71	F1Blue	M
0x72	F2Red	M
0x73	F3Green	M
0x74	F4Yellow	M
0x75	F5	M
0x76	Data	M

6.8.6. Commands

ID	Name	Direction	Response	Access	Conformance
0x00	SendKey	client ⇒ server	SendKeyResponse	O	M
0x01	SendKeyResponse	client ⇐ server	N		M

6.8.6.1. SendKey Command

Upon receipt, this SHALL process a keycode as input to the media endpoint.

If a device has multiple media endpoints implementing this cluster, such as a casting video player endpoint with one or more content app endpoints, then only the endpoint receiving the command SHALL process the keycode as input. In other words, a specific content app endpoint SHALL NOT process a keycode received by a different content app endpoint.

If a second SendKey request with the same KeyCode value is received within 200 ms, then the endpoint will consider the first key press to be a press and hold. When such a repeat KeyCode value is not received within 200 ms, then the endpoint will consider the last key press to be a release.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	KeyCode	CecKey-CodeEnum	all			M

6.8.6.1.1. KeyCode Field

This field SHALL indicate the key code to process.

6.8.6.2. SendKeyResponse Command

This command SHALL be generated in response to a SendKey command. The data for this com-