

| ID | Name                | Type                | Constraint | Quality | Fallback | Conformance |
|----|---------------------|---------------------|------------|---------|----------|-------------|
| 0  | <b>Applications</b> | list[AppInfoStruct] | all        |         |          | M           |

#### 6.13.8.14.1. Applications Field

This field indicates a set of applications that SHALL be blocked when the Content Control feature is activated.

#### 6.13.8.15. RemoveBlockApplications Command

The purpose of this command is to remove applications from the BlockApplicationList attribute.

Upon receipt of the RemoveBlockApplications command, the media device SHALL check if the applications passed in this command present in the BlockApplicationList attribute. If one or more applications in Applications field which are not present in the BlockApplicationList attribute, then a response with ApplicationNotExist error Status SHALL be returned.

| ID | Name                | Type                | Constraint | Quality | Fallback | Conformance |
|----|---------------------|---------------------|------------|---------|----------|-------------|
| 0  | <b>Applications</b> | list[AppInfoStruct] | all        |         |          | M           |

#### 6.13.8.15.1. Applications Field

This field indicates a set of applications which SHALL be removed from BlockApplicationList attribute.

#### 6.13.8.16. SetBlockContentTimeWindow Command

The purpose of this command is to set the BlockContentTimeWindow attribute.

Upon receipt of the SetBlockContentTimeWindow command, the media device SHALL check if the TimeWindowIndex field passed in this command is NULL. If the TimeWindowIndex field is NULL, the media device SHALL check if there is an entry in the BlockContentTimeWindow attribute which matches with the TimePeriod and DayOfWeek fields passed in this command. \* If Yes, then a response with TimeWindowAlreadyExist error status SHALL be returned. \* If No, then the media device SHALL assign one unique index for this time window and add it into the BlockContentTimeWindow list attribute.

If the TimeWindowIndex field is not NULL and presents in the BlockContentTimeWindow attribute, the media device SHALL replace the original time window with the new time window passed in this command.