

Status Code Value	Name
0x41	Stuck
0x42	DustBinMissing
0x43	DustBinFull
0x44	WaterTankEmpty
0x45	WaterTankMissing
0x46	WaterTankLidOpen
0x47	MopCleaningPadMissing
0x48	BatteryLow

7.2.7.2. Mode Tags

The following table defines the base and derived-cluster-specific ModeTag values.

Mode Tag Value	Name
0x0000	Auto
0x0001	Quick
0x0002	Quiet
0x0003	LowNoise
0x0004	LowEnergy
0x0005	Vacation
0x0006	Min
0x0007	Max
0x0008	Night
0x0009	Day
0x4000	Idle
0x4001	Cleaning
0x4002	Mapping

7.2.7.2.1. Idle Tag

The device is not performing any of the main operations of the other modes. However, auxiliary actions, such as seeking the charger or charging, may occur.

For example, the device has completed cleaning, successfully or not, on its own or due to a command, or has not been asked to clean after a restart.

7.2.7.2.2. Cleaning Tag

The device was asked to clean so it may be actively running, or paused due to an error, due to a pause command, or for recharging etc. If currently paused and the device can resume it will con-