

Revision	Description
1	Initial revision
2	Add constraint about changing cleaning modes while the RVC Run Mode cluster is in a non-Idle mode. ChangeToModeResponse command: StatusText must be provided for InvalidInMode status. Deprecate the OnMode attribute and the related feature map bit.
3	Remove constraint on changing cleaning modes while the RVC Run Mode cluster is in a non-Idle mode. Continue to allow InvalidInMode response for devices that do not support such mode changes.
4	Add Vacuum then Mop cleaning mode
5	DirectModeChange made non-provisional

7.3.2. Classification

Hierarchy	Role	Scope	PICS Code
Mode Base	Application	Endpoint	RVCCLEANM

7.3.3. Cluster ID

ID	Name
0x0055	RVC Clean Mode

7.3.4. Features

This cluster SHALL support the FeatureMap bitmap attribute as defined below.

Bit	Code	Feature	Conformance	Summary
0	DEPONOFF	OnOff	X	Dependency with the OnOff cluster
20	DIRECTMODECH	DirectModeChange	O	Cluster supports changing clean modes from non-Idle states

7.3.4.1. DirectModeChange Feature

This feature indicates whether the cluster implementation supports changing the clean modes while the RVC Run Mode cluster's CurrentMode attribute is set to a mode without the Idle mode tag. If the implementation does not support such a change, the ChangeToModeResponse command SHALL have the StatusCode field set to the InvalidInMode value.