

7.3.7.2. Mode Tags

The following table defines the base and derived-cluster-specific ModeTag values.

Mode Tag Value	Name
0x0000	Auto
0x0001	Quick
0x0002	Quiet
0x0003	LowNoise
0x0004	LowEnergy
0x0005	Vacation
0x0006	Min
0x0007	Max
0x0008	Night
0x0009	Day
0x4000	DeepClean
0x4001	Vacuum
0x4002	Mop
0x4003	Vacuum then Mop

7.3.7.2.1. Deep Clean Tag

While in this mode, the device is optimizing for improved cleaning.

7.3.7.2.2. Vacuum Tag

The device's vacuuming feature is enabled in this mode.

7.3.7.2.3. Mop Tag

The device's mopping feature is enabled in this mode.

7.3.7.2.4. Vacuum then Mop Tag

The device will vacuum then mop the relevant areas in this mode.

7.3.8. Mode Change Restrictions

The server MAY refuse attempts to switch the RVC Run Mode from a mode without the Idle mode tag to another non-Idle mode, as indicated by the DirectModeChange feature.

7.3.9. Mode Examples

A few examples of modes and their mode tags are provided below.