

8.13.5.7. SupportedWatts Attribute

This attribute SHALL indicate the list of power levels (in W) supported by the server.

8.13.5.8. SelectedWattIndex Attribute

This attribute SHALL indicate the index into the list of SupportedWatts of the currently selected power setting.

The index SHALL be a valid index into the SupportedWatts list.

8.13.5.9. WattRating Attribute

This attribute SHALL indicate the rating, in Watts, of the microwave power of the oven.

Supporting this attribute can assist clients in suggesting cooking settings for various foods and beverages.

8.13.6. Commands

ID	Name	Direction	Response	Access	Conformance
0x00	SetCookingParameters	client ⇒ server	Y	O	M
0x01	AddMoreTime	client ⇒ server	Y	O	O

8.13.6.1. Command Responses Impacted By the Operational State Cluster

When the [Operational State](#) cluster or a cluster derived from it is included on the same endpoint as this cluster, the server MAY respond to commands defined in this cluster with an INVALID_IN_STATE response if the server is unable to accept those command due to restrictions imposed by the current operational state of the device or other factors.

8.13.6.2. SetCookingParameters Command

This command is used to set the cooking parameters associated with the operation of the device. This command supports the following fields:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	CookMode	uint8	desc		desc	O.b+
1	CookTime	elapsed-s	1 to Max-CookTime		30	O.b+
2	PowerSetting	uint8	MinPower to MaxPower		MaxPower	[PWR- NUM].b+
3	WattSettingIndex	uint8	desc		MS	[WATTS].b+