

Value	Name	Summary	Conformance
5	Enabled	The EV is currently allowed to charge and discharge	[V2X]

9.3.7.4. FaultStateEnum Type

This data type is derived from enum8.

Value	Name	Summary	Conformance
0	NoError	The EVSE is not in an error state.	M
1	MeterFailure	The EVSE is unable to obtain electrical measurements.	M
2	OverVoltage	The EVSE input voltage level is too high.	M
3	UnderVoltage	The EVSE input voltage level is too low.	M
4	OverCurrent	The EVSE detected charging current higher than allowed by charger.	M
5	ContactWetFailure	The EVSE detected voltage on charging pins when the contactor is open.	M
6	ContactDryFailure	The EVSE detected absence of voltage after enabling contactor.	M
7	GroundFault	The EVSE has an unbalanced current supply.	M
8	PowerLoss	The EVSE has detected a loss in power.	M
9	PowerQuality	The EVSE has detected another power quality issue (e.g. phase imbalance).	M
10	PilotShortCircuit	The EVSE pilot signal amplitude short circuited to ground.	M