

may take a few seconds and is useful for some clean up purposes.

The Fault state is used to indicate that the FaultState attribute is not NoError.

A null value SHALL indicate that the state cannot be determined.

9.3.8.2. SupplyState Attribute

This attribute SHALL indicate whether the EV is currently allowed to charge from or discharge to the EVSE.

9.3.8.3. FaultState Attribute

This attribute SHALL indicate the type of fault detected by the EVSE (internally or as detected in the pilot signal).

When the SupplyState attribute is DisabledError, the FaultState attribute will be one of the values listed in [FaultStateEnum](#), except NoError. For all values of SupplyState other than DisabledError, the FaultState attribute SHALL be NoError.

9.3.8.4. ChargingEnabledUntil Attribute

This attribute SHALL indicate the time, in UTC, that the EVSE will automatically stop current flow to the EV.

A null value indicates the EVSE is always enabled for charging.

A value in the past or 0x0 indicates that EVSE charging SHALL be disabled. The attribute is only set via the payload of the [EnableCharging](#) command.

This attribute SHALL be persisted, for example a temporary power failure should not stop the vehicle from being charged.

9.3.8.5. DischargingEnabledUntil Attribute

This attribute SHALL indicate the time, in UTC, that the EVSE will automatically stop current flow from the EV.

A null value indicates the EVSE is always enabled for discharging.

A value in the past or 0x0 indicates that EVSE discharging SHALL be disabled. The attribute is only set via the payload of the [EnableDischarging](#) command.

This attribute SHALL be persisted, for example a temporary power failure should not stop the vehicle from being discharged.

9.3.8.6. CircuitCapacity Attribute

This attribute SHALL indicate the capacity that the circuit that the EVSE is connected to can provide. It is intended to allow implementation of a self-managed network of EVSEs. It is assumed that the device will allow the setting of such values by an installer.