

Mode Tag Value	Name
0x4000	NoOptimization
0x4001	DeviceOptimization
0x4002	LocalOptimization
0x4003	GridOptimization

9.8.7.1.1. NoOptimization Tag

The device prohibits optimization of energy usage management: its energy usage is determined only by the user configuration and internal device needs.

9.8.7.1.2. DeviceOptimization Tag

The device is permitted to manage its own energy usage. For example, using tariff information it may obtain.

9.8.7.1.3. LocalOptimization Tag

The device permits management of energy usage by an energy manager to optimize the local energy usage.

9.8.7.1.4. GridOptimization Tag

The device permits management of energy usage by an energy manager to optimize the grid energy usage.

9.8.8. Mode Examples

A few examples of Device Energy Management modes and their mode tags are provided below.

- For the "No Energy Management (Forecast reporting only)" mode, tags: 0x4000 (NoOptimization).
- For the "Device Energy Management" mode, tags: 0x4001 (DeviceOptimization).
- For the "Home Energy Management" mode, tags: 0x4001 (DeviceOptimization), 0x4002 (LocalOptimization).
- For the "Grid Energy Management" mode, tags: 0x4003 (GridOptimization).
- For the "Full Energy Management" mode, tags: 0x4001 (DeviceOptimization), 0x4002 (LocalOptimization), 0x4003 (GridOptimization).

9.9. Commodity Price Cluster

The Commodity Price Cluster provides the mechanism for communicating Gas, Energy, or Water pricing information within the premises.