

lation for determining overall stream allocation resources.

#### 11.2.6.9.5. RequiresHardwareEncoder Field

This field SHALL indicate if this entry requires using a hardware encoder and thus needs to be considered when determining overall stream allocation resources.

If true, the device requires an encoder from [MaxConcurrentEncoders](#) for this combination of ImageCodec, Resolution, and MaxFrameRate.

If false, the device can produce this combination without needing a dedicated encoder.

This field is only considered if [RequiresEncodedPixels](#) is true.

#### 11.2.6.10. AudioCapabilitiesStruct Type

This struct is used to express the audio capabilities of the camera.

| ID   | Name                        | Type                                   | Constraint | Quality | Fallback | Access | Conformance |
|------|-----------------------------|----------------------------------------|------------|---------|----------|--------|-------------|
| 0x00 | <b>MaxNumberOfChannels</b>  | uint8                                  | min 1      |         |          |        | M           |
| 0x01 | <b>SupportedCodecs</b>      | list[ <a href="#">AudioCodecEnum</a> ] | min 1      |         |          |        | M           |
| 0x02 | <b>SupportedSampleRates</b> | list[uint32]                           | min 1      |         |          |        | M           |
| 0x03 | <b>SupportedBitDepths</b>   | list[uint8]                            | min 1      |         |          |        | M           |

##### 11.2.6.10.1. MaxNumberOfChannels Field

This field SHALL indicate the maximum number of channels supported by an audio stream from the camera.

##### 11.2.6.10.2. SupportedCodecs Field

This field SHALL indicate the list of audio codecs from [AudioCodecEnum](#) that are supported by the camera.

##### 11.2.6.10.3. SupportedSampleRates Field

This field SHALL indicate the list of sample rates that are supported by the audio stream from the camera expressed in Hz, e.g., (48000, 32000, 16000).