

Min and TiltMax, inclusive.

- If ZoomDelta is present:
 - Add ZoomDelta to the Zoom value in MptzPosition and clip the resulting value to be between 1 and ZoomMax, inclusive.
- Initiate movement of the camera to the new values of Pan, Tilt, or Zoom.
- Set MovementState to Moving.
- Respond with the status code SUCCESS.
- Once the camera has completed the physical movement to the target values:
 - Set MovementState to Idle.
 - Update the values in MptzPosition to the new values of Pan, Tilt, and Zoom.

11.3.7.3. MPTZMoveToPreset Command

This command SHALL move the camera to the positions specified by the Preset passed. The data for this command SHALL be as follows:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PresetID	uint8	1 to MaxPresets			M

11.3.7.3.1. PresetID Field

This field SHALL match the PresetID of an entry in MptzPresets.

11.3.7.3.2. Effect on Receipt

The process below SHALL be followed by the camera when receiving this command:

- If the provided PresetID does not match an entry in MptzPresets:
 - Fail the command with the status code NOT_FOUND, and end processing with no other side effects.
- If the camera is already engaged in a command that results in a physical move, or if the camera is otherwise unable to apply new Pan, Tilt, or Zoom values:
 - Fail the command with the status code BUSY, and end processing with no other side effects.
- Initiate movement of the camera to the applicable values for Pan, Tilt, and Zoom found in the entry identified by the provided PresetID.
- Set MovementState to Moving.
- Respond with the status code SUCCESS.
- Once the camera has completed the physical movement to the target values:
 - Set MovementState to Idle.
 - Update the values in MptzPosition to the new values for Pan, Tilt, and Zoom as obtained