

from the provided PresetID prior to the initiation of movement of the camera.

11.3.7.4. MPTZSavePreset Command

This command allows creating a new preset or updating the values of an existing one. The data for this command SHALL be as follows:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PresetID	uint8	1 to MaxPresets			O
1	Name	string	max 32			M

11.3.7.4.1. PresetID Field

This field SHALL indicate the ID of an entry in [MptzPresets](#).

11.3.7.4.2. Effect on Receipt

The process below SHALL be followed by the camera when receiving this command:

- If the PresetID field is not present:
 - If the size of [MptzPresets](#) is greater than or equal to [MaxPresets](#):
 - Fail the command with the status code RESOURCE_EXHAUSTED, and end processing with no other side effects.
 - Generate a new PresetID value. This value starts at 1 and monotonically increases by 1 with each new saved preset.
 - A value incremented past [MaxPresets](#) wraps to 1.
 - The camera verifies that the incremented ID does not match any other ID. If such a match is found:
 - The ID is incremented until a unique ID is found, wrapping to 1 if the value equals [MaxPresets](#).
 - Create a new entry in [MptzPresets](#) using the new PresetID, the provided Name field, and the current values of [MptzPosition](#).
- Else:
 - If the PresetID matches an existing entry in [MptzPresets](#):
 - Update that entry using the provided Name field and the current values of [MptzPosition](#).
 - Else:
 - If the size of [MptzPresets](#) is greater than or equal to [MaxPresets](#):
 - Fail the command with the status code RESOURCE_EXHAUSTED, and end processing with no other side effects.
 - Create a new entry in [MptzPresets](#) using the provided PresetID, the provided Name field, and the current values of [MptzPosition](#).