

Value	Name	Summary	Conformance
3	UserBusy	The remote party is busy	M
4	Replaced	The call was replaced by another call	M
5	NoUserMedia	An error code when there is no local mic/camera to use. This may be because the hardware isn't plugged in, or the user has explicitly denied access	M
6	InviteTimeout	The call timed out whilst waiting for the offer/answer step to complete	M
7	AnsweredElsewhere	The call was answered from a different device	M
8	OutOfResources	The was unable to continue due to not enough resources or available streams	M
9	MediaTimeout	The call ended due to a media timeout	M
10	LowPower	The call ended due to hitting a low power condition	M
11	PrivacyMode	The call ended due to the camera being set into a privacy mode.	M
12	UnknownReason	Unknown or unspecified reason	M

11.4.5.3. ICEServerStruct Type

This type SHALL specify the [RFC 8825](#) compliant [ICE servers](#) used to facilitate the negotiation of peer-to-peer connections through NATs (Network Address Translators) and firewalls. It mimics the model used in the W3C WebRTC API [RTCIceServer](#) [<https://www.w3.org/TR/webrtc/#dom-rtciceserver>] dictionary with the addition of a Matter specific field for specifying the Root Certificate of any ICE servers that require TLS.

There are two types of ICE Servers which help to discover the public IP address of a device and relay media traffic when direct peer-to-peer communication is not possible: