

ID	Name	Type	Constraint	Quality	Fallback	Conformance
1	Transport-Status	Transport-StatusEnum	all			M

11.7.9.5.1. ConnectionID Field

This field SHALL be a [PushTransportConnectionID](#) representing the transport to modify. If null is passed, all transports belonging to the calling fabric will be modified.

11.7.9.5.2. TransportStatus Field

This field SHALL be a [TransportStatusEnum](#) and represent the new transport status to apply.

11.7.9.5.3. Effect on Receipt

The following process SHALL be followed when the server receives this command:

- If the passed in *TransportStatus* is set to Active, and the UTCTime attribute of the Time Synchronization cluster is null:
 - Fail the command with the cluster-specific status code of InvalidTime, and end processing with no other side effects.
- Create a temporary list
- If the passed in *ConnectionID* field is null:
 - For each entry in [CurrentConnections](#):
 - If the associated fabric of that entry is the accessing fabric:
 - Add the [ConnectionID](#) of that entry to the temporary list.
- Else:
 - If no entry can be found for the passed in *ConnectionID* in the [CurrentConnections](#) list:
 - Fail the command with the status code NOT_FOUND, and end processing with no other side effects.
 - If the associated fabric of that entry is not the accessing fabric:
 - Fail the command with the status code NOT_FOUND, and end processing with no other side effects.
 - Add *ConnectionID* to the temporary list
- For each [PushTransportConnectionID](#) in the temporary list:
 - If the passed in *TransportStatus* field is set to Inactive:
 - Disable transmissions on the transport identified by the id.
 - Remove any queued items for upload on the transport.
 - Terminate any uploads currently in progress by using the HTTP/2 stream cancel process, as defined in Section 6.4 of [RFC 9113](#).