

Bit index	Name	Ins tru c- tio n De pen - den cy	Description
9	Press Reset Button until light blinks	O	The Device will enter the target state when reset button is pressed until associated light blinks. Information on color of light MAY be made available via PI key (see Note 1).
10	Press Reset Button for N seconds with application of power	M	The Device will enter the target state when reset button is pressed for N seconds when applying power to it. The exact value of N SHALL be made available via PI key.
11	Press Reset Button until light blinks with application of power	O	The Device will enter the target state when reset button is pressed until associated light blinks when applying power to the Device. Information on color of light MAY be made available via PI key (see Note 1).
12	Press Reset Button N times	M	The Device will enter the target state when reset button is pressed N times with maximum 1 second between each press. The exact value of N SHALL be made available via PI key.
13	Press Setup Button	no	The Device will enter the target state when setup button is pressed.
14	Press Setup Button with application of power	no	The Device will enter the target state when setup button is pressed when applying power to it.
15	Press Setup Button for N seconds	M	The Device will enter the target state when setup button is pressed for N seconds. The exact value of N SHALL be made available via PI key.
16	Press Setup Button until light blinks	O	The Device will enter the target state when setup button is pressed until associated light blinks. Information on color of light MAY be made available via PI key (see Note 1).
17	Press Setup Button for N seconds with application of power	M	The Device will enter the target state when setup button is pressed for N seconds when applying power to it. The exact value of N SHALL be made available via PI key.
18	Press Setup Button until light blinks with application of power	O	The Device will enter the target state when setup button is pressed until associated light blinks when applying power to the Device. Information on color of light MAY be made available via PI key (see Note 1).