

```
0x67, 0x6d, 0x61, 0x53, 0x32}
```

```
Resume2MIC = Crypto_AEAD_GenerateEncrypt(
    K = S2RK,
    P = Resume2MIC_P,
    A = Resume2MIC_A,
    N = Resume2MIC_Nonce
)
```

- Any context-specific tags not listed in the above TLV schemas SHALL be reserved for future use, and SHALL be silently ignored if seen by an initiator which cannot understand them.
- The responder SHALL send a message with the **Secure Channel Protocol ID** and **Sigma2Resume Protocol Opcode** from Table 18, “Secure Channel Protocol Opcodes” whose payload is the TLV-encoded **Sigma2_Resume ResumeMsg2** with an anonymous tag for the outermost struct.

```
ResumeMsg2 =
{
    resumptionID          (1) = ResumptionID,
    sigma2ResumeMIC       (2) = ResumeMIC2,
    responderSessionID    (3) = ResponderSessionId,
    responderSessionParams (4) = session-parameter-struct (optional)
}
```

- The responder SHALL generate the session keys as described in Section 4.14.2.6.7, “Resumption Session Encryption Keys”.

Validate Sigma2_Resume

On receipt of **ResumeMsg2**, the initiator SHALL perform the following:

- The initiator SHALL **generate the S2RK key**.
- The initiator SHALL verify the **Resume2MIC** by **decrypting** the following values:

```
byte Resume2MIC_A[] = {}
byte Resume2MIC_Nonce[13] = /* "NCASE_SigmaR2" */
    {0x4e, 0x43, 0x41, 0x53, 0x45, 0x5f, 0x53, 0x69,
     0x67, 0x6d, 0x61, 0x53, 0x32}
```

```
Success, Resume2MICPayload = Crypto_AEAD_DecryptVerify(
    K = S2RK,
    C = ResumeMsg2.sigma2ResumeMIC,
    A = Resume2MIC_A,
    N = Resume2MIC_Nonce
```