

being synchronized.

- g. The **Source Node ID** field SHALL be set to the Node ID of the sender Node.
- h. The **Destination Node ID** field SHALL be set to the **Source Node ID** of the message that triggered the synchronization attempt.
2. Create a new synchronization **Exchange**.
 - a. The **Exchange ID** of the message SHALL be set to match the new Exchange.
 - b. The **I Flag** SHALL be set to **1**.
 - c. The **A Flag** SHALL be set to **0**.
 - d. The **R Flag** SHALL be set to **1**.
3. Set the *Challenge* field to the value returned by **Crypto_DRBG(len = 8 * 8)** and store that value to resolve synchronization responses from the destination peer.
4. Arm a timer to enforce that a synchronization response is received before **MSG_COUNTER_SYNC_TIMEOUT**.
 - a. Upon firing of the timer:
 - i. The synchronization exchange SHALL be closed.
 - ii. Any message waiting on synchronization associated with the exchange SHALL be discarded.
 - b. The timer SHALL be stopped upon receipt of an authenticated *MsgCounterSyncRsp* message that matches:
 - i. The **Source Node ID** field matches the **Destination Node ID** field of the most recent *MsgCounterSyncReq* message generated for that Node.
 - ii. The *Response* field corresponds to the *Challenge* field of the *MsgCounterSyncReq* message.
5. Invoke **Section 4.7.1, “Message Transmission”** using parameters from step 1 to encrypt and then send the request message over UDP to the IPv6 unicast address of the destination.
 - a. The request message SHALL use the same operational group key as the message which triggered synchronization.
 - b. The group key SHALL be known/derivable by both parties (sender and receiver).

The receiver of *MsgCounterSyncReq* SHALL:

1. Verify the **Destination Node ID** field SHALL match the Node ID of the receiver, otherwise discard the message.
2. Respond with *MsgCounterSyncRsp*.

The sender of the *MsgCounterSyncRsp* response message SHALL:

1. Set the Message Header fields as follows:
 - a. The **S Flag** SHALL be set to **1**.
 - b. The **DSIZ** field SHALL be set to **1**.