

4.19.1. BTP Session Interface

Conceptually, an open BTP session is exposed to the next-higher session layer as a full-duplex message stream.

4.19.2. BTP Frame Format

A BTP Frame consists of an 8-bit header followed by one or more optional fields, as detailed below. BTP uses little endian encoding for any header fields larger than one byte in length.

Table 28, “BTP Packet PDU format” defines the BTP Packet PDU format.

Unused fields SHALL be set to '0'.

Table 28. BTP Packet PDU format

bit 0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
Control Flags								[Management Opcode]							
[Ack Number]								[Sequence Number]							
[Message Length]															
[Segment Payload]...															
...															

4.19.2.1. Control Flags

Table 29. BTP Control Flags

bit 7	6	5	4	3	2	1	0
-	H	M	-	A	E	C	B

H (Handshake) bit

Set to '0' for normal BTP packets. When set, this bit indicates a BTP handshake packet for session establishment and has a different packet format described below.

M (Management Message) bit

Indicates the presence ('1') or absence ('0') of the Management Opcode field. All segments of a message SHALL set this bit to the same value.

A (Acknowledgement) bit

Indicates the presence of the Ack Number field.

E (Ending Segment) bit

Set to '1' on the last segment of a BTP SDU and set to '0' for all other segments of the same BTP SDU. A segment MAY have both the Beginning and Ending bits set indicating that a full BTP SDU is included in the message. When set, the segment payload length is equal to the total remaining unre-