

ceived message data. When not set, the segment payload length is equal to the maximum allowable BTP session packet size minus header overhead.

C (Continuing Segment) bit

Set to '0' on the first segment of a BTP SDU and set to '1' for all remaining segments of the same BTP SDU.

B (Beginning Segment) bit

Set to '1' on the first segment of a BTP SDU and set to '0' for all remaining segments of the same BTP SDU. It indicates the presence of the Message Length field.

4.19.2.2. Ack Number

Optional field specified in [Section 4.19.4.8, “Packet Acknowledgements”](#).

4.19.2.3. Sequence Number

Mandatory field for regular data messages specified in [Section 4.19.4.6, “Sequence Numbers”](#).

4.19.2.4. Message Length

Optional field present in Beginning Segment only. Value indicates the length in bytes of the full message buffer to be transmitted. None of the BTP Packet PDU fields is included in the Message Length.

4.19.2.5. Segment Payload

Optional field containing a segment of the Service Data Unit (SDU) message in transmission to the receiver.

4.19.3. BTP Control Frames

BTP defines different control frame formats depending on the Management Opcode that is in the BTP Packet PDU header. Valid Management Opcodes for BTP Control Frames are defined in [Table 30, “BTP Control codes”](#).

Table 30. BTP Control codes

Management Opcode	Name	Description
0x6C	Handshake	Request and response for BTP session establishment

4.19.3.1. BTP Handshake Request

Table 31. BTP Handshake Request format

bit 0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
Control Flags = 0x65								Management Opcode = 0x6C							
Ver[0]				Ver[1]				Ver[2]				Ver[3]			