

In case the size of the Matter message to transmit in the **TRANSPORT** command APDU is bigger than the maximum size that can be transmitted by this APDU, the APDU chaining procedure specified in [ISO/IEC 7816-4](#) SHALL be used, even though the **TRANSPORT** command belongs to proprietary class. Thanks to the APDU chaining procedure, the protocol can handle Matter messages up to 65535 bytes. However, the maximum size of Matter Message than can be actually transferred is limited by memory constraints of the implementation and [Message Size Requirements](#).

4.21.4.1. SELECT command

Matter commissioning SHALL be initiated by the NFC Reader/Writer by issuing the 7816-4 SELECT command with the Application Identifier (AID) 'A0 00 00 09 09 8A 77 E4 01' as shown in [Table 44](#).

Table 44. NTL SELECT command APDU

CLA	INS	P1	P2	Lc	Data (hexadecimal bytes)	Le
0x00	0xA4	0x04	0x0C	0x09	A0:00:00:09:09:8A:77:E4:01	0x00

When in commissioning mode, a commissionee SHALL answer to a correct SELECT command with a successful response APDU as shown in [Table 45](#).

Table 45. NTL SELECT Successful response APDU

Data							SW1	SW2
Version (8 bits)	0x00 (8 bits)	0x0 (4 bits)	Discriminator (12 bits)	Vendor ID (16 bits)	Product ID (16 bits)	Extended Data (0 or more bits)	0x90	0x00

Data fields:

- **Version** is a uint8 that SHALL encode the NTL protocol version supported by the commissionee. The version SHALL be 0x01. Other values SHALL be reserved for future use. The commissioner SHALL use the corresponding NTL protocol to communicate with the commissionee.
- The next 8 bits, cleared, are undefined (reserved).
- The next 4 bits, cleared, encode the format of the following fields.
- The remaining fields are described in [Section 5.4.2.4, “Discovery Information”](#).
 - Devices MAY choose not to advertise either the Vendor ID and Product ID, or only the Product ID due to privacy or other considerations. When choosing not to advertise both Vendor ID and Product ID, the device SHALL set both Vendor ID and Product ID fields to 0. When choosing not to advertise only the Product ID, the device SHALL set the Product ID field to 0. A device SHALL NOT set the Vendor ID to 0 when providing a non-zero Product ID.
 - **Extended Data** MAY be omitted.

When not in commissioning mode, a commissionee SHALL either ignore the command (no response) or answer with an error response APDU as shown in [Table 46](#) indicating that conditions of use are not satisfied.

Table 46. NTL SELECT Error response APDU