

1. UDC with IdentificationDeclaration sent to Commissioner
2. Commissioner reads instanceName, performs Commissionable Node Discovery to determine vid, pid, rotating ID, Device name, PASE IP, PASE Port
3. Commissioner prompts user for permission to commission Device name
4. User approves
5. Commissioner checks for apps granting access to the vid of the Commissionee, applies a filter on this list if the VidList in the IdentificationDeclaration is populated, and attempts to use Account Login on any resulting apps in order to obtain Passcode using rotatingID
6. If no Passcode is obtained, Commissioner prompts user to input Passcode from Commissionee, taking into account PasscodeLength field when provided in the IdentificationDeclaration
7. Commissioner attempts to commission Commissionee

5.3.7.2. UDC with Commissionable Node Discovery bypass

This saves about 1 second of latency in practice due to skipping second step (Commissionable Node Discovery) in Regular UDC.

1. UDC with IdentificationDeclaration containing VendorId, ProductId, RotatingDeviceId and Port sent to Commissioner
2. Commissioner prompts user for permission to commission Device name
3. User approves
4. Commissioner checks for apps granting access to the vid of the Commissionee, applies a filter on this list if the VidList in the IdentificationDeclaration is populated, and attempts to use Account Login on any resulting apps in order to obtain Passcode using rotatingID
5. If no Passcode is obtained, Commissioner prompts user to input Passcode from Commissionee, taking into account PasscodeLength field when provided in the IdentificationDeclaration
6. Commissioner attempts to commission Commissionee

5.3.7.3. UDC with coordinated Passcode prompt

This allows the Commissionee to wait to display the Passcode until it receives a signal from the Commissioner that a Passcode is needed. When the same user account is active on both the Commissionee (often, in a phone app) and the Commissioner (often, in a TV app), then the commissioning process can often complete without requiring the Commissionee to display a Passcode. When no Passcode is required, it can be confusing for the user if the Commissionee shows a Passcode. To address this, the Commissionee can request to be told by the Commissioner when it's Passcode input dialog is displayed to the user by sending the IdentificationDeclaration message with the CdUponPasscodeDialog set to true. Then, when a Passcode is needed, the Commissioner sends a CommissionerDeclaration with the NeedsPasscode set to true.

5.3.7.3.1. UDC with coordinated Passcode prompt, no Passcode needed

1. UDC with IdentificationDeclaration sent to Commissioner containing CdUponPasscodeDialog set to true