

are supported by the Commissioner, then the commissioner SHOULD perform the required steps described in [Enhanced Setup Flow](#) rather than following the [CommissioningCustomFlowUrl](#).

- A manufacturer contemplating using this flow should realize that
 - This flow typically requires internet access to access the URL, so initial commissioning of the device may fail if there is no internet connection at that time/location.
 - If the flow requires an app, it needs to be made available for popular platforms amongst the user population; some of their platforms running a commissioner (e.g. a smart speaker not running a popular mobile OS) may thus not be able to be used for the initial commissioning of such devices.

Table 80. Values of Ledger fields to represent Custom Commissioning Flow

Field Name	Value(s)
CommissioningCustomFlow	2 - Custom (Mandatory)
CommissioningCustomFlowUrl	'URL' - Device Manufacturer URL (Mandatory)
CommissioningModeInitialStepsHint	This field SHALL be set to a non-zero integer value with at least bit 1 set (Device Manufacturer URL). See Table 5, “Pairing and Reset Hint Values” for a complete list of pairing instructions. Example value: 2 - The following bits are set: 1 (Device Manufacturer URL) (Mandatory).
CommissioningModeInitialStepsInstruction	The field SHALL be set when CommissioningModeInitialStepsHint has a mandatory Pairing Instruction dependency and MAY be set when CommissioningModeInitialStepsHint has an optional Pairing Instruction dependency. See PI Dependency column of Pairing Hint Table to determine which pairing hints have a mandatory or optional Pairing Instruction dependency and therefore require or allow this field to be populated.

5.7.3.1. CommissioningCustomFlowUrl format

The [CommissioningCustomFlowUrl](#) MAY contain a query component (see [RFC 3986](#) section 3.4). If a query is present, it SHALL be composed of one or more key-value pairs:

- The query SHALL use the **&** delimiter between key/value pairs.
- The key-value pairs SHALL in the format **name=<value>** where **name** is the key name, and **<value>** is the contents of the value encoded with proper URL-encoded escaping.
- If key **MTcu** is present, it SHALL have a value of **"_"** (i.e. **MTcu=_**). This is the "callback URL ([Call-backUrl](#)) placeholder".