

- Access Control List has single entry: `[{Privilege: Administer, Authmode: CASE (2), Subjects: [0x0011223344556677], Targets: []}]`
- Node ID 0x0011223344556677 over CASE is allowed **Administer** privilege for all targets
- Incoming message Source is Node ID 0x0011223344556677 over CASE: matches Access Control Entry subject
- Actions:
 1. Action: Write (1st path)
 1. Path: Endpoint[0]/Cluster[AccessControl]/Attribute[ACL]/ListIndex[0]/Field[Targets]
 2. Value: `[{Endpoint: 2}]`
 - Single entry updated to target only Endpoint 2
 3. **Granted:** Administer privilege granted, due to Access Control Entry match
 2. Action: Write (2nd path)
 1. Path: Endpoint[1]/Cluster[OnOff]/Attribute[OnTime]
 2. **Denied:** No privilege granted, because prior action **in the same message** had updated Access Control List to only allow access to Endpoint 2, and this action targets Endpoint 1
- Post-conditions:
 - Access Control List has single entry, updated by first path of Write Action: `[{Privilege: Administer, Authmode: CASE (2), Subjects: [0x0011223344556677], Targets: [{Endpoint: 2}]}]`
 - Node ID 0x0011223344556677 over CASE is allowed **Administer** privilege for only Endpoint 2 target

Note that in this example, the Node has inadvertently lost its ability to update the Access Control Cluster by limiting its Administer privilege to Endpoint 2.

6.6.5. Access Control Cluster handling of Access Restrictions

In the example above, the ARL was empty, meaning that there were no access restrictions imposed upon the fabric by the device. However, the following Access Control Cluster examples illustrate how access restrictions would impact access granted to a given client.

Upon Factory Data Reset, the Access Control Cluster has an Access Control List with no entries, an Access Restriction List with no entries, and a CommissioningARL set by the device which applies during commissioning sessions.

```
Access Control Cluster: {
  ACL: [],          // empty
  Extension: [],    // empty (omitted hereafter)
  CommissioningARL: [
    0: {
      Endpoint: 1,      // application endpoint 1
      Cluster: 0x0453,  // application cluster 0x0453
    }
  ]
}
```