

```

    }
  ]
}

```

Updates to the ARL attribute can happen at any time, for example, as a result of configuration changes made by the user within an external management user interface, out of band of the Matter protocol. In particular, the fabric Administrator can request that the device initiates a review of fabric restrictions using the **ReviewFabricRestrictions** command on the Access Control Cluster. This command returns a **ReviewFabricRestrictionsResponse** containing a **Token** which can be used to correlate with a **FabricRestrictionReviewUpdate** event, indicating completion of the fabric restriction review. Such a review can result in an asynchronous update to the ARL attribute and an **AccessRestrictionEntryChanged** event.

In this example, after the fabric restriction review, the ARL value is updated: the result is a single limitation on Cluster 0x0453 of Endpoint 1: access to command 0x0000. In other words, restrictions on attributes and events on Cluster 0x0453 of Endpoint 1 have been removed, and all command restrictions on the cluster except command 0x0000 have been removed.

```

Access Control Cluster: {
  ACL: [
    ...
    1: {
      FabricIndex: 1,
      Privilege: View,
      AuthMode: CASE,
      Subjects: [],
      Targets: []
    }
  ],
  ARL: [
    ...
    1: {
      FabricIndex: 1,
      Endpoint: 1,           // application endpoint 1
      Cluster: 0x0453,       // application cluster 0x0453
      Restrictions: [
        0: {
          Type: CommandForbidden, // command limitation
          Id: 0x0000              // command 0x0000
        }
      ]
    }
  ]
}

```