

choice set SHALL be included in an implementation. n SHALL be between 1 and the number of elements in the choice set minus 1.

- If n appears with a minus ("-") sign choice parameter, n represents that at most n elements of the choice set SHALL be included in an implementation. n SHALL be between 1 and the number of elements in the choice set minus 1.
- n can appear as a range, e.g. 2-4, without a trailing plus "+" or minus "-" sign, to indicate that the number of elements included in an implementation SHALL be within the indicated range inclusive. The values in the range SHALL be between 1 and the number of elements in the choice set minus 1. If a range is used, trailing choice parameters plus "+" and minus "-" SHALL NOT be used.

When choice conformance notation is used, each element in the choice set SHALL have identical choice parameters.

Invalid example: It is illegal to use "O.a" for one element and "O.a2" for another.

Choice sets SHALL NOT be shared between tables within the same device type or cluster specification. For example, if choice set **a** is used in the Attributes table and a second choice set is used in another table within the cluster specification, the second set must use a different choice set identifier, such as **b**.

Invalid example: It is illegal to have one attribute marked as O.a in the attributes table and one command marked as O.a in the commands table.

Valid examples:

- "O.a" means exactly one of the "a" elements SHALL be supported.
- "O.a2" means exactly two of the "a" elements SHALL be supported.
- "O.a2+" means at least two of the "a" elements SHALL be supported.
- "O.a+" means at least one of the "a" elements SHALL be supported.
- "O.a2-" means at most two of the "a" elements SHALL be supported.
- "O.a-" means at most one of the "a" elements SHALL be supported.
- "O.a2-4" means 2, 3 or 4 of the "a" elements SHALL be supported.

Although individual element conformance such as "O.a", "O.a+", "[AB].a+" or "[AB].a2-4" allows an individual element to be optional, the restrictions on the choice set defined by the choice set parameters must be satisfied once the conformance expression is evaluated and an implementation SHALL support a number of elements as allowed by the choice set parameters. This may be a specific number of elements, or one of a range of possible numbers of elements, depending on the choice set parameters.

For example: The following is valid, because the n value of 1 or more is always supported.

If AB is true and CD is false then AbsoluteValue must be supported and optionally PercentValue. If AB is false and CD is true then PercentValue must be supported and optionally AbsoluteValue. If AB is true and CD is true then both elements must be supported. If AB is false and CD is false then either one or both elements must be supported.