

The purpose of this feature on the Access Control cluster is to indicate to a fabric Administrator that access by it to specific attributes, commands and/or events for specific clusters is currently prohibited. Attempts to access these restricted data model elements SHALL result in an error of ACCESS_RESTRICTED.

A device that implements this feature SHALL have a mechanism to honor the ReviewFabricRestrictions command, such as user interfaces or service interactions associated with a service provider or the device manufacturer, which allows the owner (or subscriber) to manage access restrictions for each fabric. The user interface design, which includes the way restrictions are organized and presented to the user, is not specified, but SHOULD be usable by non-expert end-users from common mobile devices, personal computers, or an on-device user interface.

Controllers and clients SHOULD incorporate generic handling of the ACCESS_RESTRICTED error code, when it appears in allowed contexts, in order to gracefully handle situations where this feature is encountered. Device vendors that adopt this feature SHOULD be judicious in its use given the risk of unexpected behavior in controllers and clients.

For certification testing, a device that implements this feature SHALL provide a way for all restrictions to be removed.

The ARL attribute provides the set of restrictions currently applied to this fabric.

The ReviewFabricRestrictions command provides a way for the fabric Administrator to request that the server triggers a review of the current fabric restrictions, by involving external entities such as end-users, or other services associated with the manager of the device hosting the server. This review process MAY involve communication between external services and the user, and MAY take an unpredictable amount of time to complete since an end-user may need to visit some resources, such as a mobile application or web site. A FabricRestrictionReviewUpdate event will be generated by the device within a predictable time period of the ReviewFabricRestrictionsResponse (see [Section 9.10.8.1, “ReviewFabricRestrictions Command”](#) for specification of this time period), and this event can be correlated with the ReviewFabricRestrictionsResponse using a token provided in both. The device MAY provide instructions or a Redirect URL in the FabricRestrictionReviewUpdate event in order to help the user access the features required for managing per-fabric restrictions.

See [Section 6.6.2, “Model”](#) for a description of how access control is impacted by the ARL attribute.

Managed Device Feature Usage Restrictions

Use of this feature SHALL be limited to the mandatory clusters of endpoints having a device type that explicitly permits its use in the Device Library Specification. As a reminder, the device types associated with an endpoint are listed in the Descriptor cluster of the endpoint.

In addition, use of this feature SHALL NOT restrict the following clusters on any endpoint:

1. the Descriptor Cluster (0x001D)
2. the Binding Cluster (0x001E)
3. the Network Commissioning Cluster (0x0031)
4. the Identify Cluster (0x0003)