

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0006	ARL	list[Access-RestrictionEntryStruct]	desc		[]	R V F	MNGD

9.10.6.1. Default Value

The default values of the Access Control Cluster ACL and Extension attributes are empty; that is, devoid of contents, with each list attribute containing zero elements.

The Access Control List is able to have an initial entry added because the [Access Control Privilege Granting algorithm](#) behaves as if, over a PASE commissioning channel during the [commissioning phase](#), the following implicit Access Control Entry were present on the Commissionee (but not on the Commissioner):

```
Access Control Cluster: {
  ACL: [
    0: {                                // implicit entry only; does not explicitly exist!
      FabricIndex: 0,                  // not fabric-specific
      Privilege: Administer,
      AuthMode: PASE,
      Subjects: [],
      Targets: []                      // entire node
    }
  ],
  Extension: []
}
```

When the [ManagedDevice](#) feature is present, the value of the Access Control Cluster CommissioningARL attribute contains the set of access restrictions applied during commissioning, before a fabric has been assigned. Upon allocation of a new FabricIndex during commissioning (see [Section 11.18.6.8, “AddNOC Command”](#)), one or more ARL entries with the new FabricIndex SHALL be added to the ARL attribute.

In the following example of the CommissioningARL and ARL attributes, the restrictions applied during commissioning consist of a single entry with 3 limitations on Cluster 0x0453 of Endpoint 1: writing to attribute 0x0000, all commands, all events. In contrast, the example also includes a restriction on the fabric with index 1 which consists of 1 limitation on Cluster 0x0453 of Endpoint 1: writing to attribute 0x0000.

```
Access Control Cluster: {
  CommissioningARL: [
    0: {
```