

9.12.10. Software update (OTA)

The Bridge is a Matter device and its Matter-related functionality MAY be updated using the mechanism described in [Section 11.20, “Over-the-Air \(OTA\) Software Update”](#).

The Bridged Devices, on the other hand, are not native Matter devices, do not have a Product ID, and are not listed in the [Distributed Compliance Ledger](#). They are typically updated using a mechanism defined and deployed by the Bridge Manufacturer. That same mechanism is typically used to update the parts of the Bridge which are not related to Matter, which is particularly relevant to allow synchronization of updates to the non-Matter part of the Bridge with updates to the Bridged Devices. Obviously, such mechanism MAY also be employed to update the entire Bridge firmware, including the Matter-related functionality.

9.12.11. Best practices for Bridge Manufacturers

This section summarizes (in order of priority) the process to determine which non-Matter devices the Bridge exposes to the Fabric.

1. Choice of supported device types

- A Manufacturer MAY choose which of the Matter device types they can or want to support in the Bridge. After implementation of support for bridging of those device types, they SHALL certify the Bridge for those device types.
- By default, a Bridge SHOULD expose to the Fabric all its connected non-Matter devices which can be mapped to a Matter device type for which that Bridge is certified.
E.g., if a Bridge is certified for Matter light bulbs, it SHOULD NOT hide any light bulb on the non-Matter side from the Fabric by default (some situations where the Bridge MAY deviate from this recommendation are in the following text).
- Given the wide variety of device types on a wide variety of standards, there may be device types on the non-Matter side that do not have a corresponding Matter device type. Such devices cannot be bridged to a Matter device type. The Manufacturer MAY choose to not expose such devices with the Bridge or MAY expose them with a manufacturer-specific device type and/or manufacturer-specific clusters.

2. Compatibility issues

- For the device types for which a Bridge is certified, a Bridge Manufacturer MAY decide to not expose certain devices based on any reason, including compatibility and interoperability reasons, or to expose them in a 'best-effort' manner as needed.
 - The Bridge Manufacturer may choose to not expose a device that does not support certain functions or features which are mandatory for a Matter device type, but which are defined as optional, or not defined at all, in the specification for the corresponding device type on the non-Matter side of the bridge. Such a Bridge would expose to the Fabric only Bridged Devices of device types which support those particular control functions or features which are required.
 - The Bridge Manufacturer may also choose to map or emulate such features which are not available in the Bridged Device; example: for a bridged colored light connected via a protocol which does not support scenes, the Bridge could emulate the scene function by storing the scenes in the Bridge and sending corresponding brightness and color com-