

- The server SHALL only keep the bridged device active once for a request. (The server SHALL only consider the operation performed if an associated ActiveChanged event was generated.)

This command SHALL have the following data fields:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	StayActiveDuration	uint32	all			M
1	TimeoutMs	uint32	30000 to 3600000			M

StayActiveDuration Field

This field SHALL indicate the duration, in milliseconds, that the device is requested to remain active, once the device becomes active again.

The value of this field MAY be longer than the value supported by the bridged device and would, typically, be used by the client to request the server of the bridged device to stay active and responsive for this period to allow a sequence of message exchanges during that period.

The client MAY slightly overestimate the duration it wants the bridged device to be active for, in order to account for network delays.

TimeoutMs Field

This field SHALL indicate the period, in milliseconds, that the server will wait before the "pending active" state expires. See the [KeepActive Command](#) description for details.

NOTE

TimeoutMs is a timeout for the request, NOT the time the device will be awake for. The server will wait for up to TimeoutMs for the device. If after TimeoutMs the ICD device does NOT check-in, the server will not perform any actions.

9.13.7. Events

ID	Name	Priority	Quality	Access	Conformance
0x00	StartUp				O
0x01	ShutDown				O
0x02	Leave				O
0x03	ReachableChanged				M
0x80	ActiveChange d	INFO		V	BIS