

9.16.6.2. ActiveModeDuration Attribute

This attribute SHALL indicate the minimum interval in milliseconds the server typically will stay in active mode after initial transition out of idle mode. The ActiveModeDuration does not include the ActiveModeThreshold.

9.16.6.3. ActiveModeThreshold Attribute

This attribute SHALL indicate the minimum amount of time in milliseconds the server typically will stay active after network activity when in active mode.

9.16.6.4. RegisteredClients Attribute

This attribute SHALL contain all clients registered to receive notification if their subscription is lost. The maximum number of entries that can be in the list SHALL be [ClientsSupportedPerFabric](#) for each fabric supported on the server, as indicated by the value of the [SupportedFabrics](#) attribute in the [Operational Credentials](#) cluster.

9.16.6.5. ICDCounter Attribute

This attribute returns the value of the ICD Counter.

9.16.6.6. ClientsSupportedPerFabric Attribute

This attribute SHALL indicate the maximum number of entries that the server is able to store for each fabric in the [RegisteredClients](#) attribute.

9.16.6.7. UserActiveModeTriggerHint Attribute

This attribute SHALL indicate which user action(s) will trigger the ICD to switch to Active mode. If the attribute indicates support for a trigger that is dependent on the [UserActiveModeTriggerInstruction](#) in the [UserActiveModeTriggerHint](#) table, the [UserActiveModeTriggerInstruction](#) attribute SHALL be implemented and SHALL provide the required information, unless specified otherwise in the requirement column of the [UserActiveModeTriggerHint](#) table.

ActuateSensorLightsBlink, ResetButtonLightsBlink and SetupButtonLightsBlink (i.e. bits 7, 9 and 14) have a dependency on the [UserActiveModeTriggerInstruction](#) attribute but do not require the attribute to be present.

Bit index	Name	Requirement	UserActiveModeTriggerInstruction Dependency
0	PowerCycle	The Device will automatically enter Active Mode upon power cycle (e.g. remove/re-insert batteries).	False