

Bit index	Name	Requirement	UserActiveModeTriggerInstruction Dependency
6	ActuateSensorTimes	The Device will enter Active Mode when reset button is pressed. The exact value of N SHALL be made available via the UserActiveModeTriggerInstruction attribute.	True
7	ActuateSensorLightsBlink	The Device will enter Active Mode when the sensor is actuated until associated light blinks. Information on color of light MAY be made available via the UserActiveModeTriggerInstruction attribute.	True
8	ResetButton	The Device will enter Active Mode when reset button is pressed.	False
9	ResetButtonLightsBlink	The Device will enter Active Mode when reset button is pressed until associated light blinks. Information on color of light MAY be made available via the UserActiveModeTriggerInstruction attribute.	True
10	ResetButtonSeconds	The Device will enter Active Mode when reset button is pressed for N seconds. The exact value of N SHALL be made available via the UserActiveModeTriggerInstruction attribute.	True