

Bit index	Name	Requirement	UserActiveModeTriggerInstruction Dependency
16	AppDefinedButton	The Device will enter Active Mode when N button is pressed where N identifies which button to press. The value of N SHALL be made available via the UserActiveModeTriggerInstruction attribute	True

An [ICD](#) can indicate multiple ways of being put into Active Mode by setting multiple bits in the bitmap at the same time. However, a device SHALL NOT set more than one bit which has a dependency on the [UserActiveModeTriggerInstruction](#) attribute.

9.16.6.8. UserActiveModeTriggerInstruction Attribute

The meaning of the attribute is dependent upon the [UserActiveModeTriggerHint](#) attribute value, and the conformance is indicated in the "dependency" column in [UserActiveModeTriggerHint table](#). The [UserActiveModeTriggerInstruction](#) attribute MAY give additional information on how to transition the device to Active Mode. If the attribute is present, the value SHALL be encoded as a valid UTF-8 string with a maximum length of 128 bytes. If the [UserActiveModeTriggerHint](#) has the [ActuateSensorSeconds](#), [ActuateSensorTimes](#), [ResetButtonSeconds](#), [ResetButtonTimes](#), [SetupButtonSeconds](#) or [SetupButtonTimes](#) set, the string SHALL consist solely of an encoding of N as a decimal unsigned integer using the ASCII digits 0-9, and without leading zeros.

For example, given [UserActiveModeTriggerHint](#)="1024", [ResetButtonSeconds](#) is set which indicates "Press Reset Button for N seconds". Therefore, a value of [UserActiveModeTriggerInstruction](#)="6" would indicate that N is 6 in that context.

When [CustomInstruction](#) is set by the [UserActiveModeTriggerHint](#) attribute, indicating presence of a custom string, the [ICD](#) SHOULD perform localization (translation to user's preferred language, as indicated in the Device's currently configured locale). The Custom Instruction option SHOULD NOT be used by an [ICD](#) that does not have knowledge of the user's language preference.

When the [UserActiveModeTriggerHint](#) key indicates a light to blink ([ActuateSensorLightsBlink](#), [ResetButtonLightsBlink](#) or [SetupButtonLightsBlink](#)), information on color of light MAY be made available via the [UserActiveModeTriggerInstruction](#) attribute. When using such color indication in the [UserActiveModeTriggerInstruction](#) attribute, the string SHALL consist of exactly 6 hexadecimal digits using the ASCII characters 0-F and encoding the RGB color value as used in HTML encodings.

9.16.6.9. OperatingMode Attribute

This attribute SHALL indicate the operating mode of the ICD as specified in the [OperatingModeEnum](#).