

Value	Name	Summary	Conformance
7	BatteryUnderVoltage	The Node detects this battery source is under voltage.	M
8	ChargerOverVoltage	The Node detects the charger for this battery source is over voltage.	M
9	ChargerUnderVoltage	The Node detects the charger for this battery source is under voltage.	M
10	SafetyTimeout	The Node detects a charging safety timeout for this battery source.	M

11.7.6.4. PowerSourceStatusEnum Type

This data type is derived from enum8.

Value	Name	Summary	Conformance
0	Unspecified	Indicate the source status is not specified	M
1	Active	Indicate the source is available and currently supplying power	M
2	Standby	Indicate the source is available, but is not currently supplying power	M
3	Unavailable	Indicate the source is not currently available to supply power	M

11.7.6.5. WiredCurrentTypeEnum Type

This data type is derived from enum8.

Value	Name	Summary	Conformance
0	AC	Indicates AC current	M
1	DC	Indicates DC current	M

11.7.6.6. BatChargeLevelEnum Type

This data type is derived from enum8.