

11.7.7.18. BatPresent Attribute

This attribute SHALL indicate whether the Node detects that the batteries are properly installed.

11.7.7.19. ActiveBatFaults Attribute

This attribute SHALL indicate the set of battery faults currently detected by the Node on this power source. This set is represented as a list of [BatFaultEnum](#). When the Node detects a fault has been raised, the appropriate [BatFaultEnum](#) value SHALL be added to this list, provided it is not already present. This list SHALL NOT contain more than one instance of a specific [BatFaultEnum](#) value. When the Node detects all conditions contributing to a fault have been cleared, the corresponding [BatFaultEnum](#) value SHALL be removed from this list. An empty list SHALL indicate there are currently no active faults. The order of this list SHOULD have no significance. Clients interested in monitoring changes in active faults MAY subscribe to this attribute, or they MAY subscribe to [BatFaultChange](#).

11.7.7.20. BatReplacementDescription Attribute

This attribute SHALL provide a user-facing description of this battery, which SHOULD contain information required to identify a replacement, such as form factor, chemistry or preferred manufacturer.

11.7.7.21. BatCommonDesignation Attribute

This attribute SHALL indicate the ID of the common or colloquial designation of the battery, as specified in [BatCommonDesignationEnum](#).

11.7.7.22. BatANSIDesignation Attribute

This attribute SHALL indicate the string representing the ANSI designation for the battery as specified in [ANSI C18](#).

11.7.7.23. BatIECDesignation Attribute

This attribute SHALL indicate the string representing the IEC designation for the battery as specified in [IEC 60086](#).

11.7.7.24. BatApprovedChemistry Attribute

This attribute SHALL indicate the ID of the preferred chemistry of the battery source as specified in [BatApprovedChemistryEnum](#).

11.7.7.25. BatCapacity Attribute

This attribute SHALL indicate the preferred minimum charge capacity rating in mAh of individual, user- or factory-serviceable battery cells or packs in the battery source.

11.7.7.26. BatQuantity Attribute

This attribute SHALL indicate the quantity of individual, user- or factory-serviceable battery cells or packs in the battery source.