

11.7.8.1. WiredFaultChange Event

The WiredFaultChange Event SHALL be generated when the set of wired faults currently detected by the Node on this wired power source changes. This event SHALL correspond to a change in value of [ActiveWiredFaults](#).

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Current	list[Wired-FaultEnum]	max 8		empty	M
1	Previous	list[Wired-FaultEnum]	max 8		empty	M

Current Field

This field SHALL represent the set of faults currently detected, as per [ActiveWiredFaults](#).

Previous Field

This field SHALL represent the set of faults detected prior to this change event, as per [ActiveWiredFaults](#).

11.7.8.2. BatFaultChange Event

The BatFaultChange Event SHALL be generated when the set of battery faults currently detected by the Node on this battery power source changes. This event SHALL correspond to a change in value of [ActiveBatFaults](#).

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Current	list[BatFault-Enum]	max 8		empty	M
1	Previous	list[BatFault-Enum]	max 8		empty	M

Current Field

This field SHALL represent the set of faults currently detected, as per [ActiveBatFaults](#).

Previous Field

This field SHALL represent the set of faults detected prior to this change event, as per [ActiveBatFaults](#).

11.7.8.3. BatChargeFaultChange Event

The BatChargeFaultChange Event SHALL be generated when the set of charge faults currently detected by the Node on this battery power source changes. This event SHALL correspond to a change in value of [ActiveBatChargeFaults](#).