

Value	Name	Summary	Conformance
7	AuthFailure	Cannot associate due to authentication failure	M
8	UnsupportedSecurity	Cannot associate due to unsupported security mode	M
9	OtherConnectionFailure	Other association failure	M
10	IPv6Failed	Failure to generate an IPv6 address	M
11	IPBindFailed	Failure to bind Wi-Fi <-> IP interfaces	M
12	UnknownError	Unknown error	M

11.9.5.5. NetworkInfoStruct Type

NetworkInfoStruct struct describes an existing network configuration, as provided in the [Networks](#) attribute.

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0	NetworkID	octstr	1 to 32				M
1	Connected	bool					M

NetworkID Field

Every network is uniquely identified (for purposes of commissioning) by a NetworkID mapping to the following technology-specific properties:

- SSID for Wi-Fi
- Extended PAN ID for Thread
- Network interface instance name at operating system (or equivalent unique name) for Ethernet.

The semantics of the NetworkID field therefore varies between network types accordingly. It contains SSID for Wi-Fi networks, Extended PAN ID (XPAN ID) for Thread networks and netif name for Ethernet networks.

NOTE

SSID in Wi-Fi is a collection of 1-32 bytes, the text encoding of which is not specified. Implementations must be careful to support reporting byte strings without requiring a particular encoding for transfer. Only the commissioner should try to potentially decode the bytes. The most common encoding is UTF-8, however this is just a convention. Some configurations may use Latin-1 or other character sets. A commissioner MAY decode using UTF-8, replacing encoding errors with "?" at the applica-