

Processing an update

If any of the parameters in the OperationalDataset are invalid, the command SHALL immediately respond with NetworkConfigResponse having NetworkingStatus status field set to a value different than Success and consistent with the error.

If validation of all parameters has succeeded, this command SHALL update the existing entry indexed by NetworkID in the [Networks](#) attribute, keeping existing position within the list.

On success, the NetworkConfigResponse command SHALL have its NetworkIndex field set to the 0-based index of the entry in the [Networks](#) attribute that was just updated, and a NetworkingStatus status field set to Success.

11.9.7.6. RemoveNetwork Command

This command is used to remove a network configuration on the network interface associated with the cluster instance.

This command SHALL remove the network configuration from the Cluster if there was already a network configuration with the same NetworkID. The relative order of the entries in the [Networks](#) attribute SHALL remain unchanged, except for the removal of the requested network configuration.

If this command is received without an armed fail-safe context (see [Section 11.10.7.2, “ArmFail-Safe”](#)), then this command SHALL fail with a FAILSAFE_REQUIRED status code sent back to the initiator.

The data for this command is as follows:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	NetworkID	octstr	1 to 32			M
1	Bread-crumb	uint64	all			O

If the [Networks](#) attribute does not contain a matching entry, the command SHALL immediately respond with NetworkConfigResponse having NetworkingStatus status field set to NetworkIdNotFound.

On success, the NetworkConfigResponse command SHALL have its NetworkIndex field set to the 0-based index of the entry in the [Networks](#) attribute that was just removed, and a NetworkingStatus status field set to Success.

NetworkID Field

This field SHALL contain the NetworkID for the entry to remove: the SSID for Wi-Fi and XPAN ID for Thread.