

On successful connection, the entry associated with the given Network configuration in the [Networks](#) attribute SHALL indicate its Connected field set to true, and all other entries, if any exist, SHALL indicate their Connected field set to false.

On failure to connect, the entry associated with the given Network configuration in the [Networks](#) attribute SHALL indicate its Connected field set to false.

The precedence order of any entry subject to ConnectNetwork SHALL NOT change within the [Networks](#) attribute.

Even after successfully connecting to a network, the configuration SHALL revert to the prior state of configuration if the CommissioningComplete command (see [Section 11.10.7.6, “CommissioningComplete”](#)) is not successfully invoked before expiry of the Fail-Safe timer.

When non-concurrent commissioning is being used by a Commissioner or Administrator, the ConnectNetworkResponse SHALL be sent with the NetworkingStatus field set to Success prior to closing the commissioning channel, even if not yet connected to the operational network, unless the device would be incapable of joining that network, in which case the usual failure path described in the prior paragraphs SHALL be followed. Once the commissioning channel is closed, if the attribute [IsCommissioningWithoutPower](#) is absent or false, the operational channel SHALL start without waiting. However, if [IsCommissioningWithoutPower](#) is true, the operational channel SHALL start automatically as soon as the device is powered up and running. It is possible that the only method to determine success of the operation is operational discovery of the Node on the new operational network. Therefore, before invoking the ConnectNetwork command, the client SHOULD re-invoke the [Arm Fail-Safe](#) command with a duration that meets the following:

1. Sufficient time to meet the minimum required time (see [Section 11.9.6.4, “ConnectMaxTimeSeconds Attribute”](#)) that may be taken by the server to connect to the desired network.
2. Sufficient time to account for possible message-layer retries when a response is requested.
3. Sufficient time to allow [operational discovery](#) on the new network by a Commissioner or Administrator.
4. Sufficient time to establish a [CASE](#) session after operational discovery
5. Not so long that, in error situations, the delay to reverting back to being discoverable for commissioning with a previous configuration would cause significant user-perceived delay.

Note as well that the CommissioningTimeout duration provided in a prior [OpenCommissioningWindow](#) or [OpenBasicCommissioningWindow](#) command may impact the total time available to proceed with error recovery after a connection failure.

The [LastNetworkingStatus](#), [LastNetworkID](#) and [LastConnectErrorValue](#) attributes MAY assist the client in determining the reason for a failure after reconnecting over a Commissioning channel, especially in non-concurrent commissioning situations.

NetworkID Field

This field SHALL contain the NetworkID for the entry used to configure the connection: the SSID for Wi-Fi and XPAN ID for Thread.