

ID	Name	Direction	Response	Access	Conformance
0x07	SetTCAC-knowledge-mentsRe-sponse	client $\leftarrow$ server	N		TC

11.10.7.1. Common fields in General Commissioning cluster responses

Some response commands have a DebugText argument which SHOULD NOT be presented directly in user interfaces. Its purpose is to help developers in troubleshooting errors. The value MAY go into logs or crash reports.

11.10.7.2. ArmFailSafe Command

This command is used to arm or disarm the fail-safe timer.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	ExpiryLengthSeconds	uint16			900	M
1	Bread-crumbs	uint64				M

Success or failure of this command SHALL be communicated by the [ArmFailSafeResponse](#) command, unless some data model validations caused a failure status code to be issued during the processing of the command.

If the [fail-safe timer](#) is not currently armed, the commissioning window is open, and the command was received over a [CASE](#) session, the command SHALL leave the current fail-safe state unchanged and immediately respond with an [ArmFailSafeResponse](#) containing an ErrorCode value of [Busy-WithOtherAdmin](#). This is done to allow commissioners, which use PASE connections, the opportunity to use the failsafe during the relatively short commissioning window.

Otherwise, the command SHALL arm or re-arm the "fail-safe timer" with an expiry time set for a duration of ExpiryLengthSeconds, or disarm it, depending on the situation:

- If ExpiryLengthSeconds is 0 and the fail-safe timer was already armed and the [accessing fabric](#) matches the Fabric currently associated with the fail-safe context, then the fail-safe timer SHALL be immediately expired (see further below for side-effects of expiration).
- If ExpiryLengthSeconds is 0 and the fail-safe timer was not armed, then this command invocation SHALL lead to a success response with no side-effects against the fail-safe context.
- If ExpiryLengthSeconds is non-zero and the fail-safe timer was not currently armed, then the fail-safe timer SHALL be armed for that duration.
- If ExpiryLengthSeconds is non-zero and the fail-safe timer was currently armed, and the [accessing Fabric](#) matches the fail-safe context's associated Fabric, then the fail-safe timer SHALL be re-armed to expire in ExpiryLengthSeconds.