

when any the following are true:

- The node doesn't support the Time Synchronization cluster.
- The node's Time Synchronization cluster instance's UTCTime attribute is null.

11.12.7.4. PayloadTestRequest Command

This command provides a means for certification tests or manufacturer's internal tests to validate particular command handling and encoding constraints by generating a response of a given size.

This command SHALL use the same **EnableKey** behavior as the **TestEventTrigger** command, whereby processing of the command is only enabled when the TestEventTriggersEnabled field is true, which SHALL NOT be true outside of certification testing or manufacturer's internal tests.

The fields for the PayloadTestRequest command are as follows:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0x00	EnableKey	octstr	16			M
0x01	Value	uint8				M
0x02	Count	uint16	max 2048			M

EnableKey field

This field SHALL have the same meaning and usage as the **TestEventTrigger EnableKey field**.

Value field

This field SHALL indicate the value to use in every byte of the PayloadTestResponse's Payload field.

Count field

This field SHALL indicate the number of times to repeat the Value in the PayloadTestResponse's Payload field.

Effect upon receipt

This command SHALL respond with a response status of CONSTRAINT_ERROR if either:

- The EnableKey field does not match the a-priori value configured on the device.
- The TestEventTriggersEnabled field is currently false.

Otherwise, the server SHALL respond with a PayloadTestResponse command with a Payload field value containing **Count** instances of the **Value** byte. If the response is too large to send, the server SHALL fail the command and respond with a response status of RESOURCE_EXHAUSTED.

For example:

- If Value is 0x55 and the Count is zero, then the PayloadTestResponse would have the Payload